

IC-M1V IC-M1EURO V



Icom's IC-M1V is the smallest and lightest waterproof* marine handheld available. Plus, it features non-corrosive construction. *equivalent to JIS waterproof specification grade 7 (1m depth for 30 min.)

Powerful 5 watts of talk power

The first in its class to use a powerful Lithium Ion battery, the IC-M1V's 5 watts can carry a conversation a long way. Charging is easy; with Lithium Ion, there's no need to fully discharge before recharging, as should be done with Ni-Cds.

Lithium Ion power = long battery life

With typical operation*, you'll get an incredible 15 to 16 hours of operating time—nearly 2 times longer than most Ni-Cds. Lithium Ion stores a charge more than 3 times longer than a typical Ni-Cd, too! *Tx:Rx: Stand-by duty ratio = 5:5:90 with BP-215L

Waterproof speaker-microphone operation

A waterproof* speaker-microphone plugs right in to the waterproof jack on top of the IC-M1V. Go where its wet without fear! *equivalent to JIS waterproof specification grade 7 (1 m depth for 30 min.)

Extra large LCD with alphanumeric indications

A large, backlit LCD offers easy to read channel numbers and descriptions. Read the IC-M1V's built-in channel descriptions, or program in your own! With up to 10 alphanumeric characters per channel, its easy to customize channel descriptives.

Flexible battery charging

Charge the IC-M1V on a boat, at home, or in the car. A self-standing battery charger comes with the radio set the charger on top of a table, or mount it to a wall. The charger accepts a variety of DC power sources*, or use the included AC adapter.

*Optional charging cable required

Fast scanning functions

"TAG" scanning offers easy, one touch channel selection and deselection. Advanced dual and tri watch scanning, normally reserved for more expensive radios, is also available.

Icom Inc.

IC-M1V·IC-M1EURO V

ADDITIONAL FEATURES

- The self check function checks internal temperature, connected battery voltage (over voltage detection), PLL lock and water intrusion
- Battery indicator shows remaining battery power in 4 levels
- · Auto WX scan and WX Alert function (USA version only)
- Simple Up/Down switches for operating channel selection
- Instant access to Ch 16 and programmable call channel

• 2 step power saver

- Kev lock function
- Automatic LCD and key backlight
- Up to 22 free channels are available (ask your local dealer for details)
- Optional voice scrambling capability (Not available in some countries)
- ATIS standard for German version

SPECIFICATIONS

GENERAL				
Frequency range (MHz) Tx Rx Usable channels*	: 156.025–157.425 156.025–163.275 : All U.S.A., International and Canadian chan- nels; plus 10 weather channels (U.S.A. only)			
• Mode	: 16K0G3E (FM)			
• Power supply requirement	nt: 7.4V DC (BP-215/L)			
Current drain (at 7.4V DC)	:			
Tx (at 5W output)	1.5A			
Rx (at AF max.)	200mA			
(at Stand-by)	20mA			
 Operating temp. range 	: -20°C to +60°C;			
	-4°F to +140°F			
 Antenna connector 	: SMA (50Ω)			
 Dimensions 	: 52.5(W)×129(H)×30(D);			
(proj. not included; mm/in)	2 ¹ / ₁₆ (W)×5 ³ / ₃₂ (H)×1 ³ / ₁₆ (D)			
• Weight (approx.; with BP-215	iL): 280g; 9.9oz			
Supplied accessories:				

Battery pack
 Battery charger
 AC adapter*

• Belt clip

TRANSMITTER				
Output power*	: 5.0W (Hi), 1.0W (Low) and 0.5W (Low2)			
Modulation system	: Variable reactance frequency modulation			
Max. Frequency deviationAudio harmonic distortion				

• Spurious emissions : IC-M1V Less than -65dB IC-M1EURO V 0.25μW

RECEIVER						
Intermediate frequencies	: 1st 2nd	21.7MHz 450kHz				
 Sensitivity 	:					
IC-M1V (12dB SINAD)	Less th	an 0.35µV				
IC-M1EURO V (20dB SINAD)	1.0µV t	ypical (emf)				
 SQL sensitivity (at threshold) 	:					
IC-M1V	Less th	an 0.35µV				
IC-M1EURO V	Less th	an 0.71µV				
 Adjacent Ch. selectivity 	:					
IC-M1V	70dB ty	/pical				

Spurious response
 IC-M1V 70dB typical
 IC-M1EURO V 70dB

 Intermodulation rejection ratio:
 IC-M1V 70dB typical
 IC-M1EURO V 68dB

 Hum and noise ratio : More than 40dB

 $\begin{tabular}{lll} \bullet & Hum and noise ratio & : More than 40dB & : 0.35W (typical at 10% distortion with an Ω load)$

Applicable U.S. Military Specifications

Icom makes rugged products that meet MIL-STD requirements and strict environmental standards as follows.

Standard	MIL 810C		MIL 810D		MIL 810E	
	Method	Proc.	Method	Proc.	Method	Proc.
High Temp.			501.2	II	501.3	II
Low Temp.			502.2	II	502.3	II
Humidity	507.1	I	507.2	II	507.3	II
Vibration	514.2	VIII, X	514.3	I	514.4	I
Shock	516.2	I, II, V	516.3	I, IV	516.4	I, IV

The IC-M1EURO V meets EMC directive. Specifications for the IC-M1V and the IC-M1EURO V are measured in accordance with EIA-152C & EIA-204D(E) and EN301-178, respectively. All stated specifications are subject to change without notice or obligation.

OPTIONS

Antenna

BP-215L Li-Ion BATTERY PACK 7.4V/1800mAh rechargeable battery pack provides 15–16 hours operatinng time. (Tx:Rx:Stand-by=5:5:90)

Same as supplied with the transceiver.

AD-95 BATTERY CHARGER + BC-122A/E/V AC ADAPTER

Regularly charges the BP-215L in 10 hours (max.). Same as supplied with the transceiver.

BC-119N DESKTOP CHARGER + AD-102 CHARGER ADAPTER

+ BC-145A/E/V AC ADAPTER

For rapidly charging of a battery pack. Charging time: 1.5–2 hours (approx).

IC-M1EURO V

BC-121N MULTI-CHARGER + AD-102 CHARGER ADAPTER

+ BC-124 AC ADAPTER

For rapidly charging of up to 6 batteries simultaneously. Charging time: 1.5–2 hours (approx)

CP-17L CIGARETTE LIGHTER CABLE or OPC-515L DC POWER CABLE For use the AD-95 or BC-119N with a DC power supply.

OPC-656 DC POWER CABLE For use the BC-121N with a DC power supply

HM-125 SPEAKER-MICROPHONE Waterproof construction, corresponds to JIS grade 7 (1 m/30 min.). An alligator type clip.

MB-88 SWIVEL BELT CLIP
Prevents accidental dropping from your belt.

UT-98 (Ver. 02) VOICE SCRAMBLER UNIT Ensures private communications. 128 scrambling codes are available. The scrambling system is not compatible with UT-112.

UT-112 VOICE SCRAMBLER UNIT Total of 32 scrambling codes available for ensuring private communication. The scrambling system is not compatible with UT-98.

* Voice scrambling units are not available in some countries. Ask your dealer for detail.





Hand strap



70dB





Icom Inc.

I - - - - (F. ... - - -) O - - I

1-1-32, Kamiminami, Hirano-ku, Osaka 547-0003, Japan Phone: 06 6793 5302 Fax: 06 6793 0013

URL: http://www.icom.co.jp/world/index.html

Count on us!

Icom America Inc.

<Corporate Headquarters> 2380 116th Avenue N.E., Bellevue, WA 98004, U.S.A. Phone: (425) 454-4155 Fax: (425) 454-1509 URL : http://www.icomamerica.com <Customer Service> Phone : (425) 454-7619

Icom Canada

Glenwood Centre #150-6165 Highway 17, Delta, B.C., V4K 5B8, Canada Phone: (604) 952-4266 Fax: (604) 952-0090 URL: http://www.icomcanada.com

Icom (Australia) Pty. Ltd.

A.B.N. 88 006 092 575 290-294 Albert Street, Brunswick, Victoria, 3056, Australia Phone: 03 9387 0666 Fax: 03 9387 0022 URL: http://www.icom.net.au

Icom New Zealand

146A Harris Road, East Tamaki, Auckland, New Zealand Phone: 09 274 4062 Fax: 09 274 4708 URL: http://www.icom.co.nz

Icom (Europe) GmbH

Communication Equipment Himmelgeister Str. 100, D-40225 Düsseldorf, Germany Phone: 0211 346047 Fax: 0211 333639 URL: http://www.icomeurope.com

Icom Spain S.L.

Crta. de Gracia a Manresa Km. 14,750 08190 Sant Cugat del Valles Barcelona, SPAIN Phone: (93) 590 26 70 Fax: (93) 589 04 46 URL: http://www.icomspain.com

Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay, Kent, CT6 8LD, U.K. Phone: 01227 741741 Fax: 01227 741742 URL: http://www.icomuk.co.uk

Icom France S.a

Zac de la Plaine, 1, Rue Brindejonc des Moulinais BP 5804, 31505 Toulouse Cedex, France Phone: (31) 5 61 36 03 03 Fax: (33) 5 61 36 03 00 URL: http://www.icom-france.com

Asia Icom Inc

6F No. 68, Sec. 1 Cheng-Teh Road, Taipei, Taiwan, R.O.C. Phone: (02) 2559 1899 Fax: (02) 2559 1874 URL: http://www.asia-icom.com

Beijing Icom Ltd.

1305, Wanshang Plaza, Shijingshan Road, Beijing, China Phone: (010) 6866 6337 Fax: (010) 6866 3553 URL: http://www.bjicom.com



Certificate Number Q14190
Icom Inc. (Japan), is an ISO9001
certification acquired company.

Your local distributor/dealer:

^{*} Varies according to version